### ASSEMBLY AND INSTALLATION (CONT.)

#### MINI PENDANT ASSEMBLY/INSTALLATION INSTRUCTIONS

#### MINI PENDANT GAL MINI PENDANT BRZ

Please read carefully and save these instructions, as you may need them at a later date.

# CAUTION

WARNING: Risk of Fire. Min 75°C supply conductors. Consult a qualified electrician to ensure correct installation.

Turn off the main power at the circuit breaker before installing the fixture, in order to prevent possible shock.

## GENERAL

All electrical connections must be in accordance with local and National Electrical Code (N.E.C.) standards. If you are unfamiliar with proper electrical wiring connections obtain the services of a qualified electrician.

Remove the fixture and the mounting package from the box and make sure that no parts are missing by referencing the illustrations on the installation instructions.


Phillips screwdriver.

# TOOLS REQUIRED

## ASSEMBLY AND INSTALLATION

#### Turn off the power at fuse or circuit breaker.

- 1. Gently take all parts out of the package, lay them on a smooth surface, unscrew the BALL NUTS and the FIXTURE SCREWS. Attach the CROSS BAR to the JUNCTION BOX using (2) MOUNTING SCREWS.
- 2. Install STEMS based on the desired length of the item, adding CEILING PLATE once finished.
- 3. Make wire connections with WIRE NUTS:
- A Connect the black wire from Fixture to the black supply wire.
- B Connect the white wire from Fixture to the white supply wire.
- C Attach the fixture ground wire to the CROSS BAR with the greenGROUND SCREW. Then connect it to the supply ground wire with a WIRE NUT. Carefully tuck wires back into the JUNCTION BOX.
- 4. Attach the CEILING PLATE to the CROSS BAR through SCREW HOLES as shown, and secure it with BALL NUTS.
- 5. Attach the SHADE to the LAMP HOLDER and secure it with SOCKET RING.
- 6. Install BULB (not included). See relamping label at socket area or packaging for maximum allowed wattage.



# *IF IN DOUBT ABOUT ELECTRICAL INSTALLATION, CONSULT A LICENSED ELECTRICIAN.*

Turn on the power at fuse or circuit breaker.